ES3000 230V 50Hz

LONG RUN ENERGY

A petrol generator designed specifically for intensive operations where performance power is demanded by professional user, over an extended period of time.

Main Features		
Frequency	Hz	50
Voltage	V	230
Power factor	cos ϕ	0.9
Phase		1

Power Rating		
Emergency Standby Power ESP	kVA	2.9
Emergency Standby Power ESP	kW	2.6
Continuous power COP	kVA	2.5
Continuous power COP	kW	2.2

Ratings definition (ISO-8528)
ESP - Emergency Standby Power:
It is the maximum power available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 200 h of operation per year with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. The permissible average power output over 24 h of operation shall not exceed 70 % of the ESP.
COP - Continuos Power:
It is defined as being the maximum power which a generating set is capable of delivering continuously for an unlimited number of hours, with the maintenance intervals and procedure being carried out as prescribed by the manufacturers.

www.pramac.com

Engine specifications		
Engine Brand		Honda
Model		GX160
Engine cooling system		Air
Displacement	cm^3	163
Aspiration		Natural
Operating Speed-Nominal	rpm	3000
Speed governor		Mechanical
Fuel		Petrol
Oil capacity	l	0.6
Starting system		Recoil

Alternator Specifications		
Alternator		NSM
Type		Brushless
Class		H
IP protection		23
Poles		2
Frequency	Hz	50
Voltage	V	230
Voltage regulation system		Capacitor
Voltage tolerance	%	+5; -10 (cosϕ1)

Dimensional data		
Length	(L) mm	623
Width	(W) mm	409
Height	(H) mm	500
Dry weight	kg	41
Fuel tank capacity	l	11

Autonomy		
Fuel consumption at 75% of Load	l/h	0.88
Fuel consumption at 100% of Load	l/h	1.17
Running time at 75% of load	h	12.50
Running time at 100% of load	h	9.40

Noise level		
Guaranteed noise level (LWA)	dB(A)	96
Noise pressure level @ 7 m	dB(A)	68

www.pramac.com

GENSET CONTROL



COMMANDS:

- Selector switch: OFF - ON
- Starting systems: Recoil
- Fuel Cock

PROTECTIONS STANDARD:

- Thermal protection
- Oil Guard

SOCKET TYPE

SCHUKO 230V 16A IP54	2

SUPPLEMENTS CONTROL (Available when ordered)

Electrical box DPP + HM



Extra Protection with:
- Differential protection 30mA
- Circuit breaker
- Hourmeter

www.pramac.com

ACCESSORIES

TRANSPORTATION KIT

- With fix handles

- With folding handles

www.pramac.com

The information is aligned with the Data file at the time of download.
Printed on 23/07/2026 (ID 2483)

©2026 | PR Industrial S.r.l. – Loc. Il Piano – 53031 Casole d'Elsa (SI) – ITALY. Company subject to the management and coordination of Generac Power Systems Inc.| All rights reserved | Image shown may not reflect actual package. Specifications subject to change without notice